



# Humidity Sensor PCE-P18 0...10V



Measures temperature and humidity / output as 0 .. 10 V signal / compact

Modbus RTU interface / wall mounting

The humidity sensor PCE-P18 is used in HVAC technology to monitor humidity and temperature. The measured values are output by the PCE-P18 humidity sensor as a 0 ... 10 V standard signal. In this compact humidity sensor, air humidity and temperature are precisely determined using a semiconductor component. For commissioning, the humidity sensor PCE-P18 is supplied via a DC voltage. The measured variables are output via a two-wire line. All connections are made via screw contacts in the waterproof IP 65 housing. In addition to the output of the measurement signal as a 0 ... 10 V signal, the measurement values can be output via the RS485 interface. This function is particularly useful if several measuring points are to be linked to one another during your home surveillance.

- Humidity and temperature sensors
- 0 ... 10 V output
- simple wall mounting
- RS-485 interface
- for permanent monitoring
- various filters available
- small dimensions - Modbus RTU

Subject to change

# Specifications

## Technical data humidity sensor PCE-P18

### humidity

measuring range	0 ... 100% RH
accuracy	± 2% (in the range 10% .... 90% RH) ± 3% (remaining range)
hysteresis	± 1% RH

### temperature

measuring range	- 20 ... 60 ° C
accuracy	± 0.7% of the measuring range
temperature effect	± 25% / 10 ° C

### Humidity sensor output

analog output	0 ... 10 V
Data Interface	RS-485 Modbus RTU
transfer mode	8N1, 8N2, 8E1, 8O1
	4800 bps
	9600 bps
baud rate	19200 bps
	38400 bps
	57600 bit / s

### General technical data for humidity sensors

supply voltage	19 V ... 30 V DC
power	<1.5 W
ambient temperature	- 30 ° C ... 85 ° C
Max. humidity	≤ 95% RH
preheat	15 minutes
degree of protection	IP 65
Assembly	wall mounting
Dimensions (wxhxd)	> 35 x 58 x 118 mm
Weight	125 g

# More information

Manual



More product info



Similar products



Subject to change