PCE Instruments

PCE Americas Inc. 711 Commerce Way Suite 8 Jupiter FL-33458 USA From outside US: +1 Tel: (561) 320-9162 Fax: (561) 320-9176 info@pce-americas.com PCE Instruments UK Ltd. Units 12/13 Southpoint Business Park Ensign way Hampshire / Southampton United Kingdom, SO31 4RF From outside UK: +44 Tel: (0) 2380 98703 0 Fax: (0) 2380 98703 9 info@pce-instruments.com

www.pce-instruments.com/english www.pce-instruments.com

Technical Specification Thermo-Hygrometer PCE-555

handheld, pocket-sized hygrometer, measures humidity, temperature,

dew point and wet bulb globe temperature

This hygrometer has been developed to take quicker measurements of humidity and temperature. The PCE-555 hygrometer also offers a calculation of dew point and information about wet bulb globe temperature. This allows for the elimination of fungus in food storage, as well as in food transportation. It is also very useful in the construction industry in order to determine condensation in walls. Thanks to its solid design, this hygrometer is ideal for taking measurements in situ, so long as the humidity sensor is not touched, not manipulated or not placed directly into liquid as it is a very sensitive component. This table perfectly illustrates the relationship that exists between dry bulb temperature, wet bulb temperature and relative humidity.

- Fast response time
- High accuracy
- Simultaneous indication of temperature and humidity
- Automatic Stiwch-off
- Calculation of dew point and wet-bulb temperature
- Background lights
- Data memory of max. value
- Compact and light

Technical specifications

Measurement ranges	0 to 100% r.h.
	-30 to 100°C
Resolution	0.01% r.h.
	0.01°C
Accuracy	±2.0% r.h. at 25°C
	±0.5°C at 25°C
Display	dual LCD with 4.5 positions
Battery	9V battery (PP3)
Response time % r.h.	about 10 sec. (90 % @ 25° C air temp.)
Dimensions	225 x 45 x 34mm
Weight	200g

Examples of use for the PCE-555 hygrometer

With the PCE-555 hygrometer you can measure ambient conditions including humidity in the top portion of the LCD and temperature shown on the bottom. It also calculates wet bulb temperature and dew point, which are useful for calculating thermal stress. There is a small video to the right which shows the device measuring humidity and temperature. This <u>link</u> shows another hygrometer which can measure relative humidity, temperature, calculate dew point and has memory for storing readings. We also have another type of <u>hygrometer</u> which can measure relative humidity, temperature, calculate dew point and has memory for storing readings. We also have another type of <u>hygrometer</u> which can measure relative humidity, temperature, calculate dew point and also measure absolute humidity with a sensor.

Dry bulb temperature is simply the environmental temperature. It's the temperature that is measured using any kind thermometer. of Wet bulb temperature is determined by using a mercury thermometer which is situated in the shade with the bulb covered with a piece of wet fabric under a current of air, measuring, for example, a vent or a rotating electric fan. In this way, the evaporation of water absorbs heat, thereby lowering the temperature, which is reflected in the decrease in the temperature reading. The lower relative humidity is, the quicker the water in the fabric will evaporate and the further the resulting decrease with respect to the dry bulb temperature. (This is used to give thermal an idea of sensation) Dew point is the temperature at which air vapour turns into condensation, producing dew or mist, or if the is low temperature enough, frost. This link has more information about temperature and the most common units of measurement in the international system of measurement relating to temperature.

Delivery Content of the Hygrometer PCE-555

PCE-555 hygrometers, carrying case, battery and user's manual